




A 2000 Series Digital Mixer Amplifier with Audio Source





The A2000 Series Digital Mixer Amplifier is a high performance cost-effective mixer power amplifier equipped with an MP3 player, Bluetooth audio function and digital FM tuner. Ideal for broadcasting, paging, or background music in schools, offices, retail shops, and religion places of prayer.

This amazing unit also provides wireless paging via an App, as well as time scheduled announcements and messages on demand remote control.



AEX App
Compatible

Available on



A 2030



A 2060



A 2150

Technical Specification

	A 2030	A 2060	A 2150
Output Power	30W (100Vline/8Ω)	60W (100Vline/8Ω)	150W (100Vline/8Ω)
Inputs	2nos. Mic (-60dB) 1nos Aux Stereo Input 1nos. Bluetooth Audio Receiver 1nos. Digital Mp3 Player (USB, SD Card Support) 1nos. FM Tuner	2nos. Mic (-60dB) 1nos Aux Stereo Input 1nos. Bluetooth Audio Receiver 1nos. Digital Mp3 Player (USB, SD Card Support) 1nos. FM Tuner	2nos. Mic (-60dB) 1nos Aux Stereo Input 1nos. Bluetooth Audio Receiver 1nos. Digital Mp3 Player (USB, SD Card Support) 1nos. FM Tuner
Frequency Response	20Hz - 20kHz	20Hz - 20kHz	20Hz - 20kHz
Total Harmonic Distortion (THD)	< 0.1% (1kHz)	< 0.1% (1kHz)	< 0.1% (1kHz)
Signal-to-Noise (SNR)	> 80dB	> 80dB	> 80dB
Power Requirement	100 ~ 240 Vac mains 50/60Hz	100 ~ 240 Vac mains 50/60Hz	100 ~ 240 Vac mains 50/60Hz
Dimensions (W x H x D)	325 x 85 x 220mm	325 x 85 x 220mm	325 x 85 x 220mm